

ELECTRIC START ENGINE
3000 r.p.m.



HONDA



3000 RPM



LWA 2000/14/CE

NOISE level



AIR cooled



GASOLINE



SINGLE phase



SINGLE phase



THREE phase

	MGTP 4,8 H BM AE	MGTP 6,5 H BM AE	MGTP 7 H BT AE
Code	PP63-5M00	PP64-7M00	PP65-7T00
On board control panel equipped with:			
	<ul style="list-style-type: none"> - Hour counter - Volt meter - Main circuit breaker - 1x16A 1ph 230V EEC socket - 1x16A 1ph 230V Schucko socket 	<ul style="list-style-type: none"> - Hour counter - Volt meter - Main circuit breaker - 1x32A 1ph 230V EEC socket - 1x16A 1ph 230V EEC socket 	<ul style="list-style-type: none"> - Hour counter - Volt meter - Main circuit breaker - 1x32A 3ph 400V EEC socket - 1x16A 1ph 230V EEC socket
Generator			
Type	Linz E1C10SF	Linz E1C10MH	Linz E1S10MH
Power	4,8 kVA 230V	6,5 kVA 230V	7 kVA 400V
Frequency	50 Hz	50 Hz	50 Hz
Engine			
Engine type	HONDA GX270	HONDA GX390	HONDA GX390
N° cylinders	1	1	1
Power	8,4 HP	11 HP	11 HP
Engine speed	3000 r.p.m.	3000 r.p.m.	3000 r.p.m.
Cooling	Air	Air	Air
Fuel	Unleaded gasoline	Unleaded gasoline	Unleaded gasoline
Starting system	Electric	Electric	Electric
Dimensions & weight			
Fuel tank capacity	5,3 lt	6,4 lt	6,4 lt
Running Time	2,7 hrs	2 hrs	2 hrs
Dry weight	85 Kg	105 Kg	105 Kg
Dimensions (L. x W. x H.)	760 x 520 x 620 mm	760 x 520 x 620 mm	760 x 520 x 620 mm

OPTIONS

<input type="checkbox"/> Site tow trailer	<input type="checkbox"/> Road tow trailer	<input type="checkbox"/> Trolley
---	---	----------------------------------

The company reserves the right to modify the technical specifications, items and design without notice.

The images of the products are indicative for illustrative purposes only.